



## DCP-L2510D Compact 3-in-1 mono laser printer



PRINT



COPY



SCAN

Print, scan and copy, quickly and quietly with the DCP-L2510D. Designed for busy home and small offices, this 3-in-1 device is both feature rich and offers great functionality in a quiet and compact unit.



## Key features:

- Fast print speeds of up to 30 pages per minute
- Automatic 2-sided print
- 250 sheet paper Input
- Up to 700 page\* in-box toner
- 64MB memory

## Performance designed for businesses of tomorrow

Designed to be set up and ready to use in minutes, the DCP-L2510D comes with fast print speeds of up to 30 pages per minute, and 250 sheet paper input.

## Maximum value for money

With cost being a key factor for many small businesses, we've ensured that the DCP-L2510D is cost-effective. Using our high-yield toner cartridges, together with 2-sided printing can seriously reduce the cost of each print job.

## Quiet without compromise

Print quietly without compromising on speed or quality, operating at the lowest decibel in class (under 50dB). The DCP-L2510D is designed to sit on your desk, printing quietly at full speed while you work without interruption.

## Designed to go the distance

Built to perform for longer. The DCP-L2510D, has been designed with you in mind. Made from robust and hardwearing materials and supported by outstanding service as standard, providing the peace of mind that your printer will keep on going.

\* Approx declared yield value in accordance with ISO/IEC 19752

## General

### Technology

Electrophotographic laser printer

### Laser classification

Class 1 laser product (IEC60825-1:2014)

### Processor

600MHz

### Memory

64MB

### Local interface

Hi-Speed USB 2.0

### Control panel

2 Line, 16 character LCD display

## Print

### Print speed standard (A4)

Up to 30ppm (pages per minute)

### Print speed 2-sided (A4)

Up to 15 sides per minute (8 sheets per minute)

### Resolution

Up to 1,200 x 1,200dpi

### Automatic 2-sided printing

Print on to both sides of the paper

### FPOT (First Print Out Time)

Less than 8.5 seconds from ready mode

### Print Languages

GDI

## Printer functions

### N-up printing<sup>3</sup>

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

### Watermark printing<sup>4</sup>

Watermark your documents with predefined text or with your own user-defined messages

### Booklet printing<sup>4</sup>

Print documents in A5 booklet format using automatic or manual 2-sided print

### Skip blank page<sup>4</sup>

Ignores any blank pages in your documents by not printing them

## Printer driver

### Windows<sup>®</sup>

Windows<sup>®</sup>10 (32 & 64 bit editions)  
Windows<sup>®</sup>8 (32 & 64 bit editions)  
Windows<sup>®</sup>7 (32 & 64 bit editions)

### Macintosh<sup>5</sup>

macOS 10.8.x or greater

### Linux<sup>5</sup>

CUPS, LPD/LPRng (32 & 64 bit editions)

## Standard paper handling

### Paper input<sup>2</sup>

Standard tray - 250 sheets  
Manual feed slot - 1 sheet

### Paper output<sup>2</sup>

Face down - 120 sheets  
Face up  
(Straight paper path) - 1 sheets

1 Approx declared yield value in accordance with ISO/IEC 19752.

2 Calculated with 80g/m<sup>2</sup> paper.

3 Windows<sup>®</sup> & Mac<sup>®</sup> only.

4 Windows<sup>®</sup> only.

5 Optional download.

6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.

For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

7 Requires Brother software.

All specifications correct at the time of printing and are subject to change.

Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

## Media specification

### Media types & weights

Standard  
Plain & recycled paper  
(between 60 - 163g/m<sup>2</sup>)  
Manual feed slot  
Plain, recycled, bond,  
label, envelope,  
(between 60 - 230g/m<sup>2</sup>)  
2-sided erint  
Plain & recycled paper  
(between 60 - 105g/m<sup>2</sup>)

### Envelope & label printing

Yes, from the Manual feed slot:  
support for 1 envelope / sheet

### Media Sizes

Standard tray  
A4, letter, A5, A5 (long edge),  
A6, executive  
Manual feed slot  
Width: 76.2mm to 215.9mm x  
Length: 127mm to 355.6mm  
2-sided Print  
A4

## Copy

### Speed - (A4)

Up to 30cpm  
(copies per  
minute)

### FCOT (First Copy Time Out)

Less than 10 seconds from  
ready mode

### Resolution

Up to 600 x 600dpi

### N in 1 copying

Allows the user to compress 2  
or 4 pages on to a single A4  
sheet

### 2in1 ID copying

Allows the user to copy both  
sides of an ID card to a  
single A4 sheet

## Scan

### Scanner type

CIS (Contact Image Sensor)

### Colour & mono scanning

Yes

### Scan speed mono

23.6 ipm (ADF)

### Scan speed colour

7.7 ipm (ADF)

### Scan resolution from scanner glass

Up to 1,200 x 1,200dpi

### Interpolated scan resolution

Up to 19,200 x 19,200dpi

### Standard functions<sup>7</sup>

Scan to e-mail, OCR, image  
& file

### Scan features

Remove background, skip  
blank page<sup>4</sup>, ID Scan<sup>4</sup>, 1 to 2  
scan<sup>4</sup>, split PDF

### Scan to SharePoint<sup>7</sup>

Scan documents directly  
into SharePoint

### Windows<sup>®</sup> web services scanning

Scan direct into Windows<sup>®</sup>  
(from Windows<sup>®</sup> 7 &  
onwards) without needing to  
install a scanner driver

## Scanner Driver

### Windows<sup>®</sup>

Windows<sup>®</sup>10  
(32 & 64 bit editions)  
Windows<sup>®</sup>8  
(32 & 64 bit editions)  
Windows<sup>®</sup>8  
(32 & 64 bit editions)

### Macintosh<sup>5</sup>

macOS 10.8.x or  
greater  
**Linux<sup>5</sup>**  
SANE(32 & 64 bit  
editions)

1 Approx declared yield value in accordance with ISO/IEC 19752.

2 Calculated with 80g/m<sup>2</sup> paper.

3 Windows<sup>®</sup> & Mac<sup>®</sup> only.

4 Windows<sup>®</sup> only.

5 Optional download.

6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.

For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.<sup>7</sup>

Requires Brother software.

All specifications correct at the time  
of printing and are subject to  
change.

Brother is a registered trademark of Brother  
Industries Ltd. Brand product names are  
respective trademarks or trademarks of  
their

## Supplies

### Inbox toner

700 pages<sup>1</sup>

### Standard yield toner

1,200 pages<sup>1</sup> (TN-2410)

### High yield toner

3,000 pages<sup>1</sup> (TN-2420)

### Drum (DR-2400)

Approx 12,000 pages

### Carton contents

Toner cartridge, drum, power supply cord, driver software for Windows®, quick set-up guide (PC interface cable NOT included)

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

## Dimensions and weights

### With carton (WxDxH)

410 x 398.5 x 272 mm - 10.3kg

### Without carton (WxDxH)

580 x 517 x 434 mm - 13.1kg

## Duty cycles

### Recommended monthly

Up to 2,000 pages monthly print volume

### Maximum monthly<sup>6</sup>

Up to 15,000 pages monthly print volume

## Environment

### Power consumption

Printing - 440W (260W in quiet mode),  
Ready - 42W,  
Sleep - 6.2W,  
Deep sleep - 0.6W,  
Off - 0.03W

### TEC Value

1.232kWh / Week

### Sound pressure level

Printing  
48dbA,  
Quiet mode printing  
44dbA,  
Ready  
Up to 30dbA

### Power saving

This enables the printer to consume less energy when not in use

### Toner saving

This reduces the toner usage and helps to reduce the total cost of printer ownership

### Energy Star

Yes

### Eco-mode

Yes

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19752.

<sup>2</sup> Calculated with 80g/m<sup>2</sup> paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows® only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products.

<sup>7</sup> For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

Requires Brother software.

All specifications correct at the time of printing and are subject to change.

Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.