HP LaserJet Pro M12w



Depend on professional quality and trusted HP performance, using the lowest-priced and smallest wireless laser printer from HP. Easily save space and budget.





Outstanding, reliable quality without compromises

- Time after time, count on documents with sharp black text from the industry leader in laser printing.²
- Help save energy with HP Auto-On/Auto-Off Technology.
- Start printing right out of the box, using a preinstalled Original HP LaserJet toner cartridge.



Efficient printing for small workspaces

- Stay productive with print speeds up to 19 pages per minute.3
- Make the most of limited workspace with this compact HP LaserJet Pro—the smallest laser printer HP
 offers
- Get high-quality pages and the performance you can count on with Original HP toner cartridges.



Well-connected printing to match the way you work9

- Easily access, print, and share resources with wireless networking.4
- Easily print from mobile devices with Android™ version 4.4 or later or Google Chrome™ operating systems.
- Print directly from your mobile device—without accessing the network.5
- Print with the ease of sending an email, right from a smartphone, tablet, or notebook, using HP ePrint.

Technical specifications

Functions	Print	
Print		
Duplex print options	Manual	
Print speed	Black (A4, normal): Up to 18 ppm; Black (letter, normal): Up to 19 ppm	
First page out	Black (A4, ready): Up to 9.2 sec; Black (A4, sleep): Up to 9.4 sec	
Print resolution	Black (best): Up to $600 \times 600 \times 2$ dpi; Black (normal): Up to $400 \times 600 \times 2$ dpi (600 dpi effective output); Black (fine lines): Up to $600 \times 600 \times 2$ dpi	
Print technology	Laser	
Print resolution technology	HP FastRes 600, HP FastRes 1200	
Print cartridges number	1 Black	
Standard print languages	Host-based printing	
Printer management	HP Status and Alerts; (CD install only)	
Connectivity		
Standard connectivity	1 Hi-Speed USB 2.0; 1 WiFi 802.11b/g/n	
Mobile printing capability	HP ePrint; Mopria™-certified; Mobile Apps	
Network ready	Standard (built-in WiFi 802.11b/g/n)	
Wireless capability	No	
Network Capabilities	None	
HP ePrint capability	Yes	
Memory	Standard: 8 MB; Maximum: 8 MB	
Processor speed	266 MHz	
Duty cycle (monthly) ⁸	Up to 5000 pages; Recommended monthly page volume⁹ : 100 to 1,000	
Paper handling	1	
Input	150-sheet input tray;	
Output	100-sheet output bin	
Media type	Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, transparencies, postcards	
Media weight	60 to 163 g/m²	
Media sizes custom	150-sheet input tray: 147 x 211 to 216 x 356 mm	
Dimensions (W x D x H) ²	349 x 238 x 196 mm	
Weight	5.2 kg	
What's in the box ¹	HP LaserJet Pro M12w Printer; Preinstalled HP Original Introductory Black LaserJet Toner Cartridge (~500 pages); Installation guide, Setup Poster, Support flyer, Warranty guide; Software drivers and documentation on CD-ROM; Power cord; USB cable	
Warranty features	One-year limited warranty	
Systems		
Compatible operating systems	Microsoft® Windows® 7, 8, 8.1,10 (32-bit/64-bit), Windows Vista® (32-bit/64-bit), Windows® XP (32-bit/64-bit), Windows® Server 2008 (32-bit/64-bit), Windows® Server 2003 (32-bit/64-bit); Mac OS X v 10.9, v 10.10, v 10.11; Apple® OS X EI Capitan (v10.11) OS X Yosemite (v10.10) OS X Mavericks (v10.9)	
Minimum system requirements	PC: Microsoft® Windows® 7, 8, 8.1,10 (32-bit/64-bit): 2 GB RAM for 64-bit, 1 GB RAM for 32-bit, 400 MB Free HD space; Windows ® VR: Intel Pentium® II, Celeron® or 233 MHz compatible processor, 750 MB Free HD space; Windows® Server 2008 (32-bit/64-bit), Windows® Server 2003: 512 MB RAM, 400 MB free HD space; all systems: CD-ROM/DVD drive or Internet connection, USB port Mac: Mac OS X 10.9, 10.10, 10.11; 1 GB available hard disk space; CD-ROM drive; USB port; Internet	
Control panel	3 LED indicator lights (Wireless, Attention, Ready); 2 buttons (Wireless, Cancel)	
Power	Power supply type: Built-in power supply; Power supply required: Input voltage 115 to 127 VAC (+/- 10%), 60 Hz (+/- Hz), 12 amp; 220 to 240 VAC (+/- 10%), 50 Hz (+/- 2 Hz), 6.0 amp; Power consumption*: 375 watts (active printing), 1.2 watts (ready), 0.8 watts (sleep), 0.8 watts (Auto Off/Wake on USB, enabled at shipment), 0.45 watts (Auto-off/Manual-or 0.45 (Manual Off); Typical electricity consumption (TEC) number* BA: 0.509 kWh/week; ES: 0.494 kWh/wk	
Software included	HP Status and Alerts, CD Launch Pad, Print Driver, Software Installer/Uninstaller	
Acoustics	Acoustic power emissions: 6.4 B(A): Acoustic Pressure Emissions Bystander (active, printing): 50 dB(A)	
Environmental ranges	Operating Temperature Range: 15 to 32.5°C; Recommended Operating Temperature: 17.5 to 25°C; Non-operating Humidity Range: 10 to 90% RH; Operating Humidity Range: 10 to 80% RH; Recommended Operating Humidity Range: 30 to 70% RH	
Safety approvals and requirements	IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12:2011+A2:2013; IEC 60825-1:2007 / EN 60825-1:2007 (Class 1 Laser/LED Product); IEC 62479:2010 / EN 62479:2010 (GB4943-2011)	
Supported network protocols	Via built-in WiFi 802.11b/g/n wireless network: IPv4, IPv6; HP ePrint	

Ordering Information

Number DescriptionTOL46A HP LaserJet Pro M12w

Supplies⁷ and Maintenance Kits

DescriptionHP 79A Black Original LaserJet Toner Cartridge (1,000 pages) CF279A

Number	Description
UG086E	HP 3 year Care Pack w/Next Day Exchange for
	LaserJet Printers
UG481E	HP 3 year Care Pack w/Onsite Exchange for
	LaserJet Printers
UG361E	HP 3 year Care Pack w/Pickup and Return
	Support for LaserJet Printers
UG289E	HP 3 year Care Pack w/Return to Depot
	Support for Laser let Printers

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to hp.com/go/cpc

HP Inc. offices

Australia	(613) 8833 5000	hp.com.au
China	(010) 6564 3888	hp.com.cn
Hong Kong	(852) 3559 7777	hp.com.hk
India	(80) 2612 9000	hp.com/in
Indonesia	(62-21) 5799 1088	hp.com/id
Korea	(02) 2199 0114	hp.co.kr
Malaysia	(603) 2332 3333	hp.com.my
New Zealand	(09) 918 9555	hp.co.nz
Philippines	(632) 888 5900	hp.com/ph
Singapore	(65) 6275 3888	hp.com.sg
Taiwan	(02) 8722 9000	hp.com.tw
Thailand	(662) 353 9500	hp.com/th
Vietnam	(848) 3823 4151	hp.com/vn

For the following countries, please fax your queries to(65) 6275 6707 Bangladesh, Bhutan, Brunei, Cambodia, Maldives, Nepal, Pakistan, Sri Lanka

Supported paper

Contact HP via phone: Asia: 65 6253 8500

Solutions

For more solutions information, please visit hp.com/go/gsc















Footnotes

- ¹ Lowest-priced claim based on manufacturer's suggested retail price (MSRP). Actual prices may vary.
- ² Based on WW market share of units shipped CY-1996 through CY-2015, WW color and monochrome laser categories. Source: IDC 2015Q4 Quarterly Hardcopy Peripheral Tracker.

 ³ Measured using ISO/IEC 24734 and excludes first set of test documents. For more information, see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- ⁴ Wireless performance is dependent on physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz routers only.

 ⁵ Feature works with devices running Android™ 4.4 or later. Mobile device needs to be connected directly to the Wi-Fi® network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile Freature works with devices running Artifician 4.4 or later. Mobile device needs to be connected under the relativistic of a wheless underectapable MFP or printing printing. Beperiting with 1.4 or advanced to the wholes are compared to MFF Alliance.

 6 Feature does not work with an iPhone. An iPad., or mobile devices running Windows. Wireless operations are compatible with 2.4 GHz operations only. App or software and HP ePrint account registration may
- also be required. Learn more at hp.com/go/mobileprinting.
- The Auto-On/Auto-Off Technology capabilities are subject to printer and settings.

 Printer requires ePrint account registration. App or software may be required. Wireless operations are compatible with 2.4 GHz operations only. Learn more at hp.com/go/mobileprinting.
- ⁹ Features are all applicable to M12w only.

Technical specifications disclaimers

- ¹ HP Original Introductory Black Laser Jet Toner Cartridge (~500 page yield). Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies. ² Without input or output trays extended

- With print cartridges

 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typicallty based on measurement of 115V device.

 5 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on

- Resident in 19 device.

 Based on the BA TEC method with the following possible exceptions: 1 minute or less sleep delay setting, Wi-Fi disabled.

 Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see http://www.hp.com/go/learnaboutsupplies.
- Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.

 9 HP recommends that the number of printed pages per month be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an
- extended warranty period.
- 10 HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit http://www.hp.com/go/SureSupply.

To learn more, visit hp.com





